

# Trek Model 5/80

## High-Voltage Power Amplifier



The Model 5/80 is a DC-stable, high-voltage power amplifier used in industrial and research applications. It features an all-solid-state design for high slew rate, wide bandwidth and low-noise operation. The four-quadrant, active output stage sinks or sources current into reactive or resistive loads throughout the output voltage range. This type of output is essential to achieve an accurate output response and high slew rate demanded by a variety of loads such as highly capacitive or reactive loads. It is configured as a non-inverting amplifier.

### Key Specifications

- |                                   |                                |
|-----------------------------------|--------------------------------|
| • Output Voltage Range:           | 0 to $\pm 5$ kV DC or peak AC  |
| • Output Current Range:           | 0 to $\pm 80$ mA DC or peak AC |
| • Slew Rate:                      | Greater than 1000 V/ $\mu$ s   |
| • Large Signal Bandwidth (-3 dB): | DC to greater than 60 kHz      |
| • DC Voltage Gain:                | Fixed at 1000 V/V              |

### Typical Applications Include

- AC or DC biasing
- Atmospheric plasma
- Dielectric barrier discharge
- Electroactive polymers (EAP)
- Electrophoresis, electrophotography
- Electrorheological fluids
- Electrostatic deflection
- Electro-optic modulation
- Ferroelectric material characterization
- Ion beam steering
- Mass spectrometers
- Material poling and particle accelerators

### Features and Benefits

- Four-quadrant output for driving capacitive loads
- Closed loop system for high accuracy
- Short-circuit protected for equipment protection
- All solid-state design for maintenance free operation
- DC-stable for programmable supply applications
- Low output noise for ultra-accurate outputs
- NIST-traceable Certificate of Calibration provided with each unit
- CE compliant (230 VAC unit only)



High Voltage Products. High Voltage Experts.

## Model 5/80 Specifications

### Performance

|                                        |                                           |
|----------------------------------------|-------------------------------------------|
| Output Voltage Range                   | 0 to $\pm 5$ kV DC or peak AC             |
| Output Current Range                   | 0 to $\pm 80$ mA DC or peak AC            |
| Input Voltage Range                    | 0 to $\pm 5$ V DC or peak AC              |
| Input Impedance                        | 10 k $\Omega$ , nominal                   |
| DC Voltage Gain                        | 1000 V/V                                  |
| DC Voltage Gain Accuracy               | Better than 0.1% of full scale            |
| DC Offset Voltage                      | Less than $\pm 2$ V                       |
| Output Noise                           | Less than 1.0 V rms*                      |
| Slew Rate (10% to 90%, typical)        | Greater than 1000 V/ $\mu$ s              |
| Large Signal Bandwidth (-3 dB)         | DC to greater than 60 kHz                 |
| Large Signal Bandwidth (3% distortion) | DC to greater 50 kHz                      |
| Small Signal Bandwidth (-3dB)          | DC to greater than 75 kHz                 |
| Settling Time                          | Less than 50 $\mu$ s for a 0 to 5 kV step |
| Stability                              |                                           |
| <i>Drift with Time</i>                 | Less than 50 ppm/hr, noncumulative        |
| <i>Drift with Temp</i>                 | Less than 200 ppm/ $^{\circ}$ C           |

### Voltage Monitor

|                   |                                            |
|-------------------|--------------------------------------------|
| Ratio             | 1/1000th of the high-voltage output signal |
| DC Accuracy       | Better than 0.1% of full scale             |
| DC Offset Voltage | Less than $\pm 2$ mV                       |
| Output Noise      | Less than 10 mV rms*                       |
| Output Impedance  | 47 $\Omega$                                |

### Current Monitor

|                  |                              |
|------------------|------------------------------|
| Ratio            | 0.1 V/mA                     |
| DC Accuracy      | Better than 1% of full scale |
| Offset Voltage   | Less than $\pm 10$ mV        |
| Output Noise     | Less than 30 mV rms*         |
| Bandwidth (-3dB) | DC to greater than 10 kHz    |
| Output Impedance | 47 $\Omega$                  |

### Features

|                     |                               |
|---------------------|-------------------------------|
| High-Voltage On/Off |                               |
| <i>Local</i>        | Individual push-button switch |

### Features (cont.)

|                    |                                                                                                                                                                                                                  |
|--------------------|------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| <i>Remote</i>      | TTL compatible input. TTL high (or open) turns off high-voltage output. TTL low turns on high-voltage output                                                                                                     |
| Dynamic Adjustment | Graduated 1-turn panel potentiometer is used to optimize the AC response for various load parameters.                                                                                                            |
| Current Limit/Trip | Switch selectable for either limit or trip. A graduated 1-turn panel potentiometer is used to adjust limit or trip level from 0 to $\pm 80$ mA                                                                   |
| Out of Regulation  | Indicator illuminates and BNC provides TTL low when the high-voltage output fails to produce required HV output (e.g. during a current limit)                                                                    |
| Trip Status        | Illuminates and a TTL low is provided when the high-voltage output is disabled due to the output current exceeding the trip level, the detection of a high-voltage supply fault for the removal of the top cover |
| Fault Status       | TTL low is provided when out of regulation for greater than 500 ms.                                                                                                                                              |

### Mechanical

|                |                                                                                                                            |
|----------------|----------------------------------------------------------------------------------------------------------------------------|
| Dimensions     | 279 mm H x 482 mm W x 654 mm D (11" H x 19" W x 25.75" D)                                                                  |
| Weight         | 24 kg (55 lb)                                                                                                              |
| HV Connector   | Alden High Voltage Connector                                                                                               |
| BNC Connectors | Amplifier Input, Voltage Monitor, Current Monitor, Remote High Voltage ON/OFF, Out of Regulation Status, Fault/Trip Status |

### Operating Conditions

|                   |                                                                         |
|-------------------|-------------------------------------------------------------------------|
| Temperature       | 0 $^{\circ}$ C to 40 $^{\circ}$ C (32 $^{\circ}$ F to 104 $^{\circ}$ F) |
| Relative Humidity | To 85%, noncondensing                                                   |
| Altitude          | To 2000 meters (6561.68 ft.)                                            |

### Electrical

|                    |                                                                                              |
|--------------------|----------------------------------------------------------------------------------------------|
| Line Voltage       | Factory Set for one of two ranges: 104 to 127 V AC or 180 to 250 V AC, either at 48 to 63 Hz |
| AC Line Receptacle | Standard three-prong AC line connector                                                       |
| Power Consumption  | 1000 VA, maximum                                                                             |

### Supplied Accessories

|                        |                                                |
|------------------------|------------------------------------------------|
| Operators' Manual      | PN: 23189                                      |
| HV Output Cable        | PN: 43406                                      |
| Line Cord, Spare Fuses | PN: N5011. Selected per geographic destination |

### Optional Accessories

|                    |                                                                               |
|--------------------|-------------------------------------------------------------------------------|
| HV Output Cable    | PN: 43421 (5m); 43422 (10 m); 43423 (20 m)                                    |
| 19" Rack Mount Kit | Model: 608RA (with EIA hole spacing)<br>Model: 608RAJ (with JIS hole spacing) |

\*Measured using the true rms feature of the HP Model 34401A digital multimeter

Copyright © 2015 TREK, INC. All specifications are subject to change. 1518/JRB



Measurement and Power Solutions™

